



Smart Control & Monitoring

- · Remote diagnosis & update via inverter
- · Auto reboot after undervoltage



Friendly & Thoughtful Design

- · Stackable auto-recognition modules
- · Plug & Play wiring



Superb Safety & Reliability

- · Reliable LFP technology with high cycle stability
- · IP55 protection for outdoor installation safety



Flexible & Adaptable Applications

- · Flexible capacity and stackable modules
- · Up to 8 towers in parallel (230kWh)



	LX F6.4-H-20	LX F9.6-H-20	LX F12.8-H-20	LX F16.0-H-20	LX F19.2-H-20	LX F22.4-H-20	LX F25.6-H-20	LX F28.8-H-2	
Technical Data	*The module a	t the top of the towe	er is the Power Con	trol Unit (PCU).				0	
Usable Energy (kWh)*1	6.4	9.6	12.8	16	19.2	22.4	25.6	28.8	
Number of PCU	1								
Number of Modules	2	3	4	5	6	7	8	9	
Battery Module	LX F3.2-20: 64V 3.2kWh								
Cell Type	LFP (LiFePO4)								
Nominal Voltage (V)	128 ^{*3}	192	256	320	384	448	512	576	
Operating Voltage Range (V	7) 114.8 ~ 144.4	172.2 ~ 216.6	229.6 ~ 288.8	287.0 ~ 361.0	344.4 ~ 433.2	401.8 ~ 505.4	459.2 ~ 577.6	516.6 ~ 649.8	
Nominal Dis- / Charge Current (A)*2	35								
Nominal Power (kW) ²	4.48	6.72	8.96	11.20	13.44	15.68	17.92	20.16	
Operating Temperature Range (°C)	Charge: 0 ~ +50; Discharge: -20 ~ +50								
Relative Humidity	0 ~ 95%								
Max. Operating Altitude (m	3000								
Communication	CAN								
Weight (kg)	86	120	154	188	222	256	290	324	
Dimensions (W × D × H mm)	600 × 380 × 559	600 × 380 × 715	600 × 380 × 871	600 × 380 × 1027	600 × 380 × 1183	600 × 380 ×1339	600 × 380 × 1495	600 × 380 × 1651	
Ingress Protection Rating	IP55 (Outdoor / Indoor)								
Mounting Method				Grou	nded				
Safety	IEC62619, IEC62040-1, IEC63056, VDE2510, CE, CEC								
Standard and EMC Certification	CE, RCM								
Transportation	1	UN38.3							

^{*1:} Test conditions, 100% DOD, 0.2C charge & discharge at +25 ±2°C for battery system at beginning life.System Usable Energy may vary with different Inverter.

*2: Nominal Dis- / Charge Current and power derating will occur related to Temperature and SOC.

*3: The start-up voltage of the LX F6.4-H-20 is insufficient to start the ET (15-30kW) inverters.

*: Please visit GoodWe website for the latest certificates.

*: All pictures shown are for reference only. Actual appearance may vary.